

## Secvest Wireless Indoor Siren

Art.-Nr. FUSG50010

---



- 
- For acoustic support of control panel and wireless outdoor sounder
  - Loud sounder (90 dB(A) @ 1 m)
  - 12 V external power supply for operation without batteries (optional)
  - Any number of indoor sirens can be integrated into the Secvest wireless alarm system
- 

### **Reliable warning for indoor areas**

The Secvest wireless indoor sounder is an optional Secvest accessory. As a purely acoustic sounder, it supports the wireless outdoor sounder and Secvest alarm panel with a signal tone of 90 dB sound pressure in the event of an alarm. The sounder and alarm panel communicate at 868.6625 MHz, a wireless frequency exclusively reserved for the security industry. The wireless indoor sounder can be powered by battery or a power supply unit. If batteries are used, the sounder has a service life of approx. 2 years. The sounder indicates when the battery life is coming to an end.

## Secvest Wireless Indoor Siren

Art.-Nr. FUSG50010

### Technical Data

Battery type	3x 1.5V LR20 battery
Connections	12V
DC voltage supply	4,5/12V
Environmental class	II
Height	208mm
Housing material	ABS
IP protection class	54
Installation location	Indoors
Length	60mm
Max. battery life	2year(s)
Max. humidity	75%

Max. operating temperature	50°C
Max. receiving range (building)	30m
Max. receiving range (outdoors)	100m
Min. operating temperature	-10°C
Modulation	FM
Radio frequency	868,6625
Sound pressure	90dB
Voltage monitoring	Yes
Width	122mm